

Control elements and connections X-CPU-3



LEDs

RUN	GREEN	Operating status RUN
	RED	Operating status STOP
ERR	RED	Error
COM	GREEN	Communication
USR	GR/RD	User

Switch

MRES	Fully delete
STOP	Cyclic program processing off
RUN	Cyclic program processing on

Starting behaviour

1. Power on
2. After 10 seconds → **COM** green
3. After 25 seconds → **RUN** green or red

Fully deleted module

After 5 seconds of confirming the switch “**MRES**”, the module will be fully deleted.

Default IP-Addresses after fully delete

ETH1: 192.168.0.90; ETH2: 192.168.1.90
 ETH3: 192.168.2.90; ETH4: 192.168.3.90

Ethernet- Connection

At the ETH1...ETH4 a network connection for the respective internal CP may be established.

You can find all product information in our download area on our homepage www.abcit.eu